

MTFR1B - FW.3.3

REGISTERS MODBUS - RTU:

READ REGISTERS (INPUT REGISTERS)

| ADDRESS | FORMAT | MULTIPLIER | UNIT | PARAMETERS |
|---------|--------|------------|------|---|
| 0000 | USHORT | 0.001 | - | Cosφ actual L1 |
| 0001 | USHORT | 0.001 | - | Cosφ actual L2 |
| 0002 | USHORT | 0.001 | - | Cosφ actual L3 |
| 0003 | ULONG | 0.1 | V | Effective tension L1-N |
| 0005 | ULONG | 0.1 | V | Effective tension L2-N |
| 0007 | ULONG | 0.1 | V | Effective tension L3-N |
| 0009 | ULONG | 0.1 | V | Effective tension L1-L2 (concatenated) |
| 000B | ULONG | 0.1 | V | Effective tension L2-L3 (concatenated) |
| 000D | ULONG | 0.1 | V | Effective tension L3-L1 (concatenated) |
| 000F | ULONG | 0.01 | A | Effective current L1 |
| 0011 | ULONG | 0.01 | A | Effective current L2 |
| 0013 | ULONG | 0.01 | A | Effective current L3 |
| 0015 | LONG | 1 | var | Real reactive power L1 (negative=capacitive) |
| 0017 | LONG | 1 | var | Real reactive power L2 (negative=capacitive) |
| 0019 | LONG | 1 | var | Real reactive power L3 (negative=capacitive) |
| 001B | ULONG | 1 | W | Real active power L1 |
| 001D | ULONG | 1 | W | Real active power L2 |
| 001F | ULONG | 1 | W | Real active power L3 |
| 0021 | ULONG | 1 | VA | Real apparent power L1 |
| 0023 | ULONG | 1 | VA | Real apparent power L2 |
| 0025 | ULONG | 1 | VA | Real apparent power L3 |
| 0027 | USHORT | 1 | % | Tension THD L1 |
| 0028 | USHORT | 1 | % | Tension THD L2 |
| 0029 | USHORT | 1 | % | Tension THD L3 |
| 002A | USHORT | 1 | % | Current THD L1 |
| 002B | USHORT | 1 | % | Current THD L2 |
| 002C | USHORT | 1 | % | Current THD L3 |
| 002D | USHORT | - | bits | Various alarms: (0 = Disabled, 1 = Enabled) |
| | | | | bit0 = A.HU - Tension too high bit4 = A.TH - High THD |
| | | | | bit1 = A.LU - Tension too low bit5 = A.CS - Cosφ min. |
| | | | | bit2 = A.HI - Current too high bit6 = A.FR - Wrong frequency |
| | | | | bit3 = A.OT - Over temperature |
| 000C | USHORT | - | bits | Eeprom alarms: (0 = Disabled, 1 = Enabled) |
| | | | | bit0 = A.PS - Error parameters setup bit4 = A.SS - Error parameter set |
| | | | | bit1 = A.PC - Calibration error parameters bit5 = A.SC - Not used |
| | | | | bit2 = A.PU - Various parameters eError bit6 = A.SU - Calibration error |
| | | | | bit3 = A.EE - Eeprom error cancellation |
| 002F | USHORT | 1 | °C/F | Temperature |
| 0030 | USHORT | - | - | Real quadrant L1 (1=IND-LOAD, 2=IND-GEN, 3=CAP-GEN, 4=CAP-LOAD) |
| 0031 | USHORT | - | - | Real quadrant L2 (1=IND-LOAD, 2=IND-GEN, 3=CAP-GEN, 4=CAP-LOAD) |
| 0032 | USHORT | - | - | Real quadrant L3 (1=IND-LOAD, 2=IND-GEN, 3=CAP-GEN, 4=CAP-LOAD) |
| 0033 | ULONG | 1 | h | Total work hours |
| 0035 | USHORT | 1 | V | Max effective tension L1 |
| 0036 | USHORT | 1 | V | Max effective tension L2 |
| 0037 | USHORT | 1 | V | Max effective tension L3 |
| 0038 | ULONG | 1 | A | Max effective current L1 |
| 003A | ULONG | 1 | A | Max effective current L2 |
| 003C | ULONG | 1 | A | Max effective current L3 |

| | | | | |
|------|--------|------|-------|--|
| 003E | USHORT | 1 | % | Max current THD L1 |
| 003F | USHORT | 1 | % | Max current THD L2 |
| 0040 | USHORT | 1 | % | Max current THD L3 |
| 0041 | USHORT | 1 | °C/°F | Max temperature |
| 0042 | USHORT | - | - | Firmware checksum |
| 0043 | USHORT | 1 | V | Max effective tension L1-L2 (concatenated) |
| 0044 | USHORT | 1 | V | Max effective tension L2-L3 (concatenated) |
| 0045 | USHORT | 1 | V | Max effective tension L3-L1 (concatenated) |
| 0046 | USHORT | 0.01 | Hz | Frequency |

READ / WRITE REGISTERS (HOLDING REGISTERS)

| ADDRESS | FORMAT | MULTIPLIER | UNIT | RANGE | PARAMETERS |
|---------|--------|------------|-------|-----------------|--|
| 0000 | ULONG | 1 | A | 5...50000 | P.01 - TA current |
| 0002 | ULONG | 0.01 | 0.01% | 40...10000 | P.02 - Tension transformer ratio |
| 0004 | USHORT | 0.01 | - | 60...360 | P.03 - Power integration time in seconds |
| 0005 | USHORT | 0.01 | - | 1...20 | P.04 - Average filter in seconds |
| 0006 | USHORT | - | - | 0 / 1 | A.01 - 0 = Three-Phase, 1 = Single-Phase |
| 0007 | USHORT | 1 | V | 220...440 | A.02 - General rated tension |
| 0008 | USHORT | - | - | 1...2 | A.03 - Polarity TA L1 (1 = in phase, 2 = inverted) |
| 0009 | USHORT | - | - | 1...2 | A.03 - Polarity TA L2 (1 = in phase, 2 = inverted) |
| 000A | USHORT | - | - | 1...2 | A.03 - Polarity TA L3 (1 = in phase, 2 = inverted) |
| 000B | USHORT | - | - | 1...2 | A.04 - Frequency (1 = 50Hz, 2 = 60Hz) |
| 000C | USHORT | - | - | 0...247 | A.05 - Serial address (0 = OFF, 1-99 = ON) |
| 000D | USHORT | - | - | 0...1 | A.06 - Temperature scale (0 = °C, 1 = °F) |
| 000E | USHORT | - | - | 0...15 | A.08 - Serial protocol type |
| 000F | USHORT | - | % | 0 / 110...150 | A.HU - Alarm (0 = disable, >0 = enable) |
| 0010 | USHORT | - | % | 0 / 80...95 | A.LU - Alarm (0 = disable, >0 = enable) |
| 0011 | USHORT | - | A | 0 / 50...50000 | A.HI - Alarm (0 = disable, >0 = enable) |
| 0012 | USHORT | - | °C/°F | 0 / 30...140 | A.OT - Alarm (0 = disable, >0 = enable) |
| 0013 | USHORT | - | units | 0 / 5...200 | A.TH - Alarm (0 = disable, >0 = enable) |
| 0014 | USHORT | 0.01 | units | 0 / 50...95 | A.CS - Alarm (0 = disable, >0 = enable) |
| 0015 | USHORT | - | Hz | 0 / 1...5 | A.FR - Alarm (0 = disable, >0 = enable) |
| 0016 | USHORT | - | units | 1...240 | A.HU - Time delay alarm |
| 0017 | USHORT | - | units | 1...240 | A.LU - Time delay alarm |
| 0018 | USHORT | - | units | 1...240 | A.HI - Time delay alarm |
| 0019 | USHORT | - | units | 1...240 | A.OT - Time delay alarm |
| 001A | USHORT | - | units | 1...240 | A.TH - Time delay alarm |
| 001B | USHORT | - | units | 1...240 | A.CS - Time delay alarm |
| 001C | USHORT | - | units | 1...240 | A.FR - Time delay alarm |
| 001D | USHORT | - | bits | 0...255 | Alarm Scale (0 = seconds, 1 = minutes) (bit0 = A.HU, bit1 = A.LU, bit2 = A.HI, bit6 = A.OT) (bit7 = A.TH, bit9 = A.CS, bit10 = A.FR) |
| 001E | - | - | - | - | Reserved |
| 001F | - | - | - | - | Reserved |
| 0020 | - | - | - | - | Reserved |
| 0021 | - | - | - | - | Reserved |
| 0022 | - | - | - | - | Reserved |
| 0023 | - | - | - | - | Reserved |
| 0024 | - | - | - | - | Reserved |
| 0025 | USHORT | - | - | 0...3 | A.HI - Controlled phase for alarm (0 = ALL, 1 = L1, 2 = L2, 3 = L3) |
| 0026 | ULONG | 1 | Wh | 0 ...4294967295 | Imported active energy L1 |
| 0028 | ULONG | 1 | Wh | 0 ...4294967295 | Imported active energy L2 |
| 002A | ULONG | 1 | Wh | 0 ...4294967295 | Imported active energy L3 |
| 002C | ULONG | 1 | varh | 0 ...4294967295 | Imported inductive reactive power energy L1 |
| 002E | ULONG | 1 | varh | 0 ...4294967295 | Imported inductive reactive power energy L2 |
| 0030 | ULONG | 1 | varh | 0 ...4294967295 | Imported inductive reactive power energy L3 |

| | | | | | |
|------|--------|---|------|-----------------|---|
| 0032 | ULONG | 1 | varh | 0 ...4294967295 | Imported capacitive reactive energy L1 |
| 0034 | ULONG | 1 | varh | 0 ...4294967295 | Imported capacitive reactive energy L2 |
| 0036 | ULONG | 1 | varh | 0 ...4294967295 | Imported capacitive reactive energy L3 |
| 0038 | ULONG | 1 | VAh | 0 ...4294967295 | Imported inductive apparent power L1 |
| 003A | ULONG | 1 | VAh | 0 ...4294967295 | Imported inductive apparent power L2 |
| 003C | ULONG | 1 | VAh | 0 ...429496729 | Imported inductive apparent power L3 |
| 003E | ULONG | 1 | VAh | 0 ...4294967295 | Imported capacitive apparent power L1 |
| 0040 | ULONG | 1 | VAh | 0 ...4294967295 | Imported capacitive apparent power L2 |
| 0042 | ULONG | 1 | VAh | 0 ...4294967295 | Imported capacitive apparent power L3 |
| 0044 | ULONG | 1 | Wh | 0 ...4294967295 | Exported active energy L1 |
| 0046 | ULONG | 1 | Wh | 0 ...4294967295 | Exported active energy L2 |
| 0048 | ULONG | 1 | Wh | 0 ...4294967295 | Exported active energy L3 |
| 004A | ULONG | 1 | varh | 0 ...4294967295 | Exported inductive reactive power energy L1 |
| 004C | ULONG | 1 | varh | 0 ...4294967295 | Exported inductive reactive power energy L2 |
| 004E | ULONG | 1 | varh | 0 ...4294967295 | Exported inductive reactive power energy L3 |
| 0050 | ULONG | 1 | varh | 0 ...4294967295 | Exported capacitive reactive energy L1 |
| 0052 | ULONG | 1 | varh | 0 ...4294967295 | Exported capacitive reactive energy L2 |
| 0054 | ULONG | 1 | varh | 0 ...4294967295 | Exported capacitive reactive energy L3 |
| 0056 | ULONG | 1 | VAh | 0 ...4294967295 | Exported inductive apparent power L1 |
| 0058 | ULONG | 1 | VAh | 0 ...4294967295 | Exported inductive apparent power L2 |
| 005A | ULONG | 1 | VAh | 0 ...4294967295 | Exported inductive apparent power L3 |
| 005C | ULONG | 1 | VAh | 0 ...4294967295 | Exported capacitive apparent power L1 |
| 005E | ULONG | 1 | VAh | 0 ...4294967295 | Exported capacitive apparent power L2 |
| 0060 | ULONG | 1 | VAh | 0 ...4294967295 | Exported capacitive apparent power L3 |
| 0062 | USHORT | - | bits | 0 ...2047 | Reset counters and maximum values: bit0 = Max tension L-N bit1 = Max current bit2 = Max THD I bit3 = Max temperature bit4 = Max THD V bit5 = Max tension L-L bit6 = Active energy bit7 = Reactive energy bit8 = Apparent energy bit9 = All import energy bit10 = All export energy |

Available optional communication module PC-USB / RS485 / TTL

Order Code: SCUSB485

